


IW 120

SMALL HEATERS

PRODUCT-NO.: 229339

Quartz heaters supply pleasant radiated IR warmth. These are ideally suited to heating smaller rooms and create a pleasantly warm space on cooler evenings on your patio. The pivoting highly polished reflector targets the heat where you need it most. You can feel the radiated heat as soon as you switch the heater on. For that reason, they are the ideal heat source in bathrooms, on covered patios or in conservatories. Highly heat-resistant quartz rods ensure a long service life. A pull switch controls the ON/OFF functions.



The main features

Infrared quartz radiant heater with 1.2 kW heating output

Immediately pleasant radiated heat

Choice of three heating stages (0.4 / 0.8 / 1.2 kW)

Easy to adjust and operate

Metal casing

Applications: e.g. bathrooms, conservatories, covered patios



Type	IW 120	IW 180
Part no.	229339	229340

Heating output

Rated heating output P_{nom}	1,2 kW	
Minimum heat output (standard value) P_{min}	0 kW	
Maximum continuous heating output $P_{max,c}$	1,2 kW	

Auxiliary power consumption

D heating output $e_{l_{max}}$	0,000 kW	
Heat output $e_{l_{min}}$	0,000 kW	
Dby mode $e_{l_{SB}}$	0,000 kW	

Type of heating output/room temperature control

Single stage heating output, no room temperature control	-	
Two or more manually adjustable stages, no room temperature control	x	
Room temperature control with mechanical thermostat	-	
With electronic room temperature control	-	
Electronic room temperature control and time of day control	-	
Electronic room temperature control and day of week control	-	

Other control options

Room temperature control with occupancy detection	-	
Room temperature control with open window detection	-	
With remote control option	-	
With adaptive control for start of heating	-	
With restricted operating times	-	
With black bulb sensor	-	

Contact information

You have questions? We appreciate to help you:

Call **+49 5531 - 7020**

Write an email to **info@stiebel-eltron.com**

Installation information

Please ask your local power supply utility or a registered electrician to install appliances that are not fully wired, i.e. ready to plug in. The electrician should also be able to assist you with obtaining the agreement of the respective power supply utility required for the appliance installation.