

SHU 10 SLi

SMALL WATER HEATER

PRODUCT-NO.: 229473

Enjoy hot water together

This model of small water heater is a real all-rounder. If required, the undersink appliance can supply multiple draw-off points with hot water simultaneously. This is particularly useful in your bathroom: several members of your family can enjoy hot water at their washbasin at the same time, whether they are cleaning their teeth, washing their hands or cleansing their face.

The pressure-tested undersink solution can be combined with most pressure taps. Thanks to its compact dimensions, the small water heater is ideal if there is limited space under your washbasin.



SHU 5 SLi

Product-No.: 222151

The main features

Variable temperature selection in the range of 35 - 82 °C

Safe use due to adjustable mechanical temperature limit as anti-scalding protection

Optimised DHW heating for higher efficiency with ECO mode

Suitable for multiple draw-off points

Very high mixed water amount



Type	SHU 5 SLi	SHU 10 SLi
Part no.	222151	229473

Technical data

Connected load	2 kW	2 kW
Rated output 2	2.0 kW	2.0 kW
Power supply	1/N/PE	1/N/PE
Rated voltage	230 V	230 V
Fuse protection 2	10 A	10 A
Frequency	50-60 Hz	50-60 Hz
Energy efficiency class (A+ → F)	A	A
Standby energy consumption/24 h at 65 °C	0.29 kWh	0.36 kWh
Nominal capacity	5 l	10 l
Mixed water amount at 40 °C	10 l	19 l
Temperature setting range	35 - 82 °C	35 - 82 °C
Version	Small water heater	Small water heater
Type	pressurised	pressurised
Installation type	Undersink	Undersink
With tap	-	-
Colour	white	white
Cable length	0.6 m	1 m
Operation	manual	manual
Temperature limit	•	•
IP rating	IP24 D	IP24 D
Height	421 mm	504 mm

Width	263 mm	295 mm
Depth	230 mm	275 mm
Weight	5.20 kg	7.60 kg

Contact information

You have questions? We appreciate to help you:

Call **+49 5531 - 7020**

Write an email to **info@stiebel-eltron.com**

Installation information

Please ask your local power supply utility or a registered electrician to install appliances that are not fully wired, i.e. ready to plug in. The electrician should also be able to assist you with obtaining the agreement of the respective power supply utility required for the appliance installation.